

CR500 Color Sensor

he distance independence (sensor head - target) is a particular feature of the CR500 which is achieved by the patented CROMLADIST® technology. The measurement distance is real time detected and compensated numerically through a specially shaped and with the color sensor firmly connected optical fiber. The distance dependent color error ΔE can be reduced by up to 97%, depending on the color. As with the other color sensors of the CROMLAVIEW® family the CR500 processes colors perceptually (i.e. according to human



color perception) and assesses color distances with the precision of the human eye.

The CR500 can be parameterized by means of RS232 or USB interfaces. The free software CR-Tool – CR500 facilitates the parameterization of the color sensor and the visualization of color values. A distance monitor supports the adjustment of the fiber head. Besides that, the color sensor can also be operated using the buttons. Therefore the distance monitoring can be performed by means of 12 LEDs.

As all the other CROMLAVIEW[®] color sensors the CR500 is equipped with CROMLASTAB[®]-technology, which protects from temperature- and aging drifts and ensures with this method a reliable operation over the whole lifetime cycle.

The sensor contains an own white light source clocked with a frequency of up to 2 kHz. Sampling takes place in both, the light and the dark phase. Additive ambient light cannot change the difference between the light and dark phase, so that the sensor is independent from ambient light.

Key Features

- Distance compensated color recognition CROMLADIST[®]
- Up to 350 colors can be stored
- Quick response time from 100 μs
- 12 channels, with binary encoding 4096 output combinations
- Long-term stability of color recognition without new teach-in by CROMLASTAB[®]technology
- Finest color differences can be detected (ΔE < 1)

Applications

- Checking functional and color coatings
- Color inspection for quality assurance
- Sorting tasks of colored parts with different hights


Options and accessory

- CR-TBox
- CR-COMBox
- USB cable



Internal Stabilization Internal Stabilization channel 1 Internal Distance compensation channel Internal Distance compensation channel Distance compensation CROMLASTAB* Distance compensation CROMLADIST*, can be switched off Receiving detector Three range photo diode Sensitivity fixed Receiving signal resolution 3 x 4096 steps Objecti Illumination High-power white light LED Ambient light compensation permanent Standard interfaces 2 Switching outputs 2 Control inputs Serial (RS232) USB USB Displays 19 LEDs for outputs, status and distance monitoring Buttons 3 buttons for Teach-In Color resolution AE _{Lin} < 1 Response time 2 100 µs On-/Off-Delay Oms	Sensing channels	1 Sensing channel
Drift stabilizationCROMLASTAB®Distance compensationCROMLADIST®, can be switched offReceiving detectorThree range photo diodeSensitivityfixedReceiving signal resolution3 x 4096 stepsObject illuminationHigh-power white light LEDAmbient light compensationpermanentStandard interfaces12 Switching outputs 2 Control inputs Serial (RS232) USBDisplays19 LEDs for outputs, status and distance monitoringButtons3 buttons for Teach-InColor resolutionAfLas < 1		5
Drift stabilizationCROMLASTAB®Distance compensationCROMLADIST®, can be switched offReceiving detectorThree range photo diodeSensitivityfixedReceiving signal resolution3 x 4096 stepsObject illuminationHigh-power white light LEDAmbient light compensationpermanentStandard interfaces12 switching outputs 2 control inputs Serial (RS232) USBDisplays19 LEDs for outputs, status and distance monitoringButtons3 buttons for Teach-InColor resolutionAfLas < 1		1 Internal Distance compensation channel
Receiving detectorThree range photo diodeSensitivityfixedReceiving signal resolution3 x 4096 stepsObject illuminationHigh-power white light LEDAmbient light compensationpermanentStandard interfaces12 Switching outputs2 Control inputs Serial (RS232) USBDisplays9 LEDs for outputs, status and distance monitoringButtons3 buttons for Teach-InColor resolutionAELab <1	Drift stabilization	
Receiving detectorThree range photo diodeSensitivityfixedReceiving signal resolution3 x 4096 stepsObject illuminationHigh-power white light LEDAmbient light compensationpermanentStandard interfaces12 Switching outputs2 Control inputs Serial (RS232) USBDisplays9 LEDs for outputs, status and distance monitoringButtons3 buttons for Teach-InColor resolutionAELab <1	Distance compensation	CROMLADIST [®] , can be switched off
SensitivityfixedReceiving signal resolution3 x 4096 stepsObject illuminationHigh-power white light LEDAmbient light compensationpermanentStandard interfaces12 Switching outputs 2 Control inputs Serial (RS232) USBDisplays19 LEDs for outputs, status and distance monitoringButtons3 buttons for Teach-InColor resolutionAE _{Lub} < 1		
Receiving signal resolution3 x 4096 stepsObject illuminationHigh-power white light LEDAmbient light compensationpermanentStandard interfaces12 Switching outputs 2 Control inputs Serial (RS232) USBDisplays19 LEDs for outputs, status and distance monitoringButtons3 buttons for Teach-InColor resolutionAELas < 1		
Object IlluminationHigh-power white light LEDAmbient light compensationpermanentStandard interfaces12 Switching outputs 2 Control inputs Serial (RS232) USBDisplays19 LEDs for outputs, status and distance monitoringButtons3 buttons for Teach-InColor resolutionAELab <1	•	3 x 4096 steps
Ambient light compensationpermanentStandard interfaces12 Switching outputs 2 Control inputs Serial (RS232) USBDisplays19 LEDs for outputs, status and distance monitoringButtons3 buttons for Teach-InColor resolutionAELab < 1		•
Initial and the property2 Control inputsSerial (RS232)USBDisplays19 LEDs for outputs, status and distance monitoringButtons3 buttons for Teach-InColor resolutionΔE _{Lab} < 1	Ambient light compensation	
Serial (RS232) USBDisplays9 LEDs for outputs, status and distance monitoringButtons3 buttons for Teach-InColor resolution $AE_{Lab} < 1$ Response time> 100 µSOn-/Off-Delay0 ms 65535 msFortection standard0% 250 %Color output channels0% 250 %Power supply18 28 VDC, max 500 mACoupling in signal pathVia optical fiberCoupling in signal path100 mm × 70 mm × 30 mm	Standard interfaces	12 Switching outputs
USBDisplays19 LEDs for outputs, status and distance monitoringButtons3 buttons for Teach-InColor resolutionΔEtab < 1		2 Control inputs
Displays19 LEDs for outputs, status and distance monitoringButtons3 buttons for Teach-InColor resolution $\Delta E_{tab} < 1$ Response time> 100 μsOn-/Off-Delay0 ms 65535 msHysteresis0 % 250 %Color output channels12, up to 350 with binary encodingProtection standardIP 54Power supply18 28 VDC, max 500 mACase temperature during operation-10 °C 55 °CCoupling in signal pathVia optical fiberCase material100 mm × 70 mm × 30 mm		Serial (RS232)
Buttons3 buttons for Teach-InButtons3 buttons for Teach-InColor resolutionΔE _{Lab} < 1		USB
Color resolutionΔELab < 1Response time> 100 μsOn-/Off-Delay0 ms 65535 msHysteresis0 % 250 %Color output channels0 % 250 with binary encodingProtection standardIP 54Power supply18 28 VDC, max 500 mACase temperature during operation-10 °C 55 °CCoupling in signal pathVia optical fiberCase materialAluminium, anodizedCase size100 mm × 70 mm × 30 mm	Displays	19 LEDs for outputs, status and distance monitoring
Response time≥ 100 μsOn-/Off-Delay0 ms 65535 msHysteresis0 % 250 %Color output channels12, up to 350 with binary encodingProtection standardIP 54Power supply18 28 VDC, max 500 mACase temperature during operation-10 °C 55 °CCoupling in signal pathVia optical fiberCase materialAluminium, anodizedCase size100 mm × 70 mm × 30 mm	Buttons	3 buttons for Teach-In
On-/Off-Delay O ms65535 ms Hysteresis 0 %250 % Color output channels 12, up to 350 with binary encoding Protection standard IP 54 Power supply 1828 VDC, max 500 mA Case temperature during operation -10 °C55 °C Coupling in signal path Via optical fiber Case material Aluminium, anodized Case size 100 mm × 70 mm × 30 mm	Color resolution	$\Delta E_{Lab} < 1$
Hysteresis0 % 250 %Color output channels12, up to 350 with binary encodingProtection standardIP 54Power supply18 28 VDC, max 500 mACase temperature during operation-10 °C 55 °CCoupling in signal pathVia optical fiberCase materialAluminium, anodizedCase size100 mm × 70 mm × 30 mm	Response time	≥ 100 µs
Color output channels12, up to 350 with binary encodingProtection standardIP 54Power supply18 28 VDC, max 500 mACase temperature during operation-10 °C 55 °CCoupling in signal pathVia optical fiberCase materialAluminium, anodizedCase size100 mm × 70 mm × 30 mm	On-/Off-Delay	0 ms 65535 ms
Protection standardIP 54Power supply18 28 VDC, max 500 mACase temperature during operation-10 °C 55 °CCoupling in signal pathVia optical fiberCase materialAluminium, anodizedCase size100 mm × 70 mm × 30 mm	Hysteresis	0 % 250 %
Power supply18 28 VDC, max 500 mACase temperature during operation-10 °C 55 °CCoupling in signal pathVia optical fiberCase materialAluminium, anodizedCase size100 mm × 70 mm × 30 mm	Color output channels	12, up to 350 with binary encoding
Case temperature during operation-10 °C 55 °CCoupling in signal pathVia optical fiberCase materialAluminium, anodizedCase size100 mm × 70 mm × 30 mm	Protection standard	IP 54
Coupling in signal pathVia optical fiberCase materialAluminium, anodizedCase size100 mm × 70 mm × 30 mm	Power supply	18 28 VDC, max 500 mA
Case material Aluminium, anodized Case size 100 mm × 70 mm × 30 mm	Case temperature during operation	-10 °C 55 °C
Case size 100 mm × 70 mm × 30 mm	Coupling in signal path	Via optical fiber
	Case material	Aluminium, anodized
Weight Approx. 260 g	Case size	100 mm × 70 mm × 30 mm
	Weight	Approx. 260 g

Typical behavior of compensation for CROMLAVIEW CR500 with CROMLADIST on ColorChecker test color target



Diagrams are showing color signal changing in ΔE due to distance changing of the fiber head from approx. ±3 mm around a nominal distance of approx. 4 mm for 24 color fields of the known color target ColorChecker[®]. Red curves depict the signal changing with activated distance compensation CROMLADIST[®]. Blue curves are depicting uncompensated signals for comparison reasons.

Vers. 1.1 (2015-10-20), 18-3024-02, Datasheet_CR500_EN_V1.1.docx